


VeeX Pod Manual

STRUCTURE



SPECIFICATION

Size: 103.8*28*18mm
Cartridge capacity: 2ml
Battery capacity: 1000mAh
Screen size: 0.49inch
Material: Aluminum alloy + PCTG
Spec of coils:
0.6Ω 20-28W
1.0Ω 12-18W

GUIDANCE

1. FILLING JUICE

Fill the e-juice into the cartridge.



TIPS

- 1) After filling the e-juice into a new cartridge, please wait for at least 5-8 minutes before vaping to avoid dry burning.
- 2) After filling the juice, please close as soon as possible to avoid leaking.

2. POWER ON/OFF

Press the fire button 5 times consecutively to turn on/off the device.

3. VAPE

After 5-8 minutes of filling the e-juice into the cartridge, you could draw to vape directly or press the fire button to vape.

4. ADJUST THE AIRFLOW

Slide the airflow adjusting valve to adjust the airflow.

5. ADJUST THE WATTAGE

Press the fire button 3 times. When the power on the screen is flashing, press the fire button to adjust the power. Every time you press, the power will be changed by 0.5w. Long press to quickly adjust the power.

The chip will generate the power range according to the resistance of coil to protect the coil from burning. The power range of 0.6Ω pod is 5-28W and 1.0Ω pod is 5-18W.

6. CHARGING

Connect the charging cable to the Type-C port to charge with the charge current of 1A. After fully charged, please cut off the power in time.

7. PUFF CLEAR

Without a cartridge installed, long - press the Fire button for

5 seconds to clear the puff count, and the device will prompt "PUFF CLEAR".

8. LOCK/UNLOCK FIRE BUTTON

Press the fire button 4 times to lock/unlock the fire button. You may still auto draw vape or press the fire button 3 times to adjust the wattage.

SCREEN PROMPTS

LOW BATTERY - The battery is low.

NO ATOMIZER - The cartridge is not detected.

SYSTEM OFF - The device is power off.

SYSTEM ON - The device is power on.

LOW RES: The short-circuit is detected.

OVER TIME - The vaping time is over 10s.

TOO HOT WARNING - The temperature of PCBA is too high.

RECOMMENDED E-JUICE

Freebase Nic 18mg - 24mg

Salt Nic 20 - 50mg

STATEMENT

1. Please keep away from inflammable and explosive materials to avoid injury.
2. Please don't leave the device unattended while charging